

test level must be no less than the environment that the rotor lead or booster charge experiences when installed and the ordnance interrupter is subjected to the ordnance interrupter's qualification environment.

(3) A high-temperature storage test is optional. A lot will have an initial service-life of five years if it passes this test and all the required tests. A lot will have an initial service-life of one year if it passes all the required tests, but does not undergo this test.

(4) The same 21 sample components, from the same lot, must be subjected to each test designated with an X. For tests designated with a lessor quantity, each component tested must be one of the original 21 sample components.