

- (2) This test must subject the component to the qualification environmental test levels. For a rotor lead or booster charge that is internal to an ordnance interrupter, the test level must be no less than the environment that the rotor lead or booster charge experiences when installed and the ordnance interrupter is subjected to ordnance interrupter's qualification environment.
- (3) For each column, the quantity of sample components required at the top of the column must be from the same production lot and must undergo each test designated with an X. For a test designated with a lessor quantity, each component must be one of the original samples for that column.
- (4) Five sample components from the same lot must undergo each test required by this column to extend the service-life of the remaining components from the same lot for one year.
- (5) Ten components from the same lot must undergo each test required by this column to extend the service-life of the remaining components from the same lot for five years.